



 PRODUCT-DETAILS

MS132-0.4

MS132-0.4 Manual Motor Starter 0.25 ... 0.40 A



General Information

| | |
|-----------------------|--|
| Extended Product Type | MS132-0.4 |
| Product ID | 1SAM350000R1003 |
| EAN | 4013614400032 |
| Catalog Description | MS132-0.4 Manual Motor Starter 0.25 ... 0.40 A |

| | |
|------------------|---|
| Long Description | <p>The MS132-0.4 manual motor starter (also known as motor protection circuit breaker or manual motor protector) is a compact 45 mm width device with a rated operational current of $I_e = 0.40$ A. This device is used to manually switch on and off motors and to protect them reliably and without the need for a fuse from short-circuits, overload and phase failures. The manual motor starter offers a rated service short-circuit breaking capacity $I_{cs} = 100$ kA at 400 VAC and trip class 10. Further features are the built-in disconnect function, temperature compensation, trip-free mechanism and a rotary handle with a clear switch position indication. The manual motor starter is suitable for three- and single-phase applications. The handle is lockable to protect against unauthorized changes. Auxiliary contacts, signaling contacts, undervoltage releases, shunt trips, 3-phase bus bars, power in-feed blocks and terminal spacers are available as accessory.</p> |
|------------------|---|

Ordering

| | |
|------------------------|---------|
| Minimum Order Quantity | 1 piece |
|------------------------|---------|

Customs Tariff Number

85362010

Popular Downloads

| | |
|-----------------------------------|------------------------------------|
| Data Sheet, Technical Information | 2CDC131021D0202 |
| Instructions and Manuals | 2CDC131022M6802 |
| Instructions and Manuals (Part 2) | 2CDC131060M0202 |
| Ex Operating Instructions | 2CDC131063M6801 |
| Time-Current Characteristic Curve | 1SAM300505F0103 |
| I ² t Characteristic | 1SAM300507F0001 1SAM300507F0003 |
| Cut-off Current Characteristic | 1SAM300508F0001 1SAM300508F0003 |
| CAD Dimensional Drawing | 2CDC001079B0201 |
| Dimension Diagram | 1SAM300402F0001 |

Dimensions

| | |
|----------------------------|----------|
| Product Net Width | 45 mm |
| Product Net Height | 90 mm |
| Product Net Depth / Length | 86.75 mm |
| Product Net Weight | 0.215 kg |

Technical

| | |
|---|---|
| Rated Service Short-Circuit Breaking Capacity (I _{cs}) | (230 V AC) 100 kA (250 V DC) 3 Poles in Series 10 kA (400 V AC) 100 kA (440 V AC) 100 kA (500 V AC) 100 kA (690 V AC) 100 kA |
| Rated Ultimate Short-Circuit Breaking Capacity (I _{cu}) | (230 V AC) 100 kA (400 V AC) 100 kA (440 V AC) 100 kA (500 V AC) 100 kA (690 V AC) 100 kA |
| Rated Instantaneous Short-Circuit Current Setting (I _i) | 5 A |
| Setting Range | 0.25 ... 0.40 A |
| Rated Operational Power AC-3 (P _e) | (400 V) Three Phase 0.09 kW |
| Rated Operational Power AC-3e (P _e) | (400 V) Three Phase 0.09 kW |
| Rated Operational Voltage | Main Circuit 690 V AC Main Circuit 250 V DC |
| Rated Operational Current (I _e) | 0.4 A |
| Rated Operational Current AC-3 (I _e) | 0.4 A |
| Rated Operational Current AC-3e (I _e) | 0.4 A |

| | |
|--|---|
| Rated Operational Current DC-5 (I_e) | 0.4 A |
| Rated Frequency (f) | Main Circuit 50 Hz Main Circuit 60 Hz |
| Operating Frequency (f _{sw}) | 0 ... 400 Hz |
| Rated Impulse Withstand Voltage (U_{imp}) | Main Circuit 6 kV |
| Rated Insulation Voltage (U_i) | 690 V |
| Power Loss | at Rated Operating Conditions per Pole 0.6 ... 1.7 W |
| Number of Poles | 3 |
| Conventional Free-air Thermal Current (I_{th}) | Main Circuit 0.4 A |
| Degree of Protection | Housing IP20 Main Circuit Terminals IP10 |
| Pollution Degree | 3 |
| Electrical Durability | 50000 cycle |
| Mechanical Durability | 100000 cycle |
| Terminal Type | Screw Terminals |
| Connecting Capacity Main Circuit | Flexible with Ferrule 1/2x 0.75 ... 2.5 mm ² Flexible with Insulated Ferrule 1/2x 0.75 ... 2.5 mm ² Flexible 1/2x 0.75 ... 2.5 mm ² Rigid 1/2x 1 ... 4 mm ² |
| Tightening Torque | Main Circuit 0.8 ... 1.2 N·m |
| Wire Stripping Length | Main Circuit 9 mm |
| Recommended Screw Driver | Pozidriv 2 |
| Mounting Position | 1 ... 6 |
| Mounting on DIN Rail | TH35-15 (35 x 15 mm Mounting Rail) acc. to IEC 60715 TH35-7.5 (35 x 7.5 mm Mounting Rail) acc. to IEC 60715 |
| Minimum Mounting Distance | Electrical Conductive Board, Horizontal - Up to 400 V 0 mm Electrical Conductive Board, Horizontal - Up to 690 V 1.5 mm Electrical Conductive Board, Vertical 75 mm Other Device Same Type, Horizontal 0 mm Other Device Same Type, Vertical 150 mm |
| Actuator Type | Rotary Handle |
| Contact Position Indication | ON / OFF / TRIP |
| Standards | IEC/EN 60947-1 IEC/EN 60947-2 IEC/EN 60947-4-1 UL 60947-1 UL 60947-4-1 IEC 60335-2-40 A2L |
| Remarks | UL508 Self-Protected Combination Motor Controller (Type E) in combination with feeder block S1-M3-xx |

Technical UL/CSA

| | | |
|-------------------------------------|---|-------|
| Short-Circuit Current Rating (SCCR) | Manual Self-Protected Combination Controllers (Type E), (480Y / 277 V AC) | 65 kA |
| | Manual Self-Protected Combination Controllers (Type E), (600Y / 347 V AC) | 47 kA |
| | Any UL Listed Fuses or Circuit-Breakers, Group Installations (480 V AC) | 65 kA |
| | Any UL Listed Fuses or Circuit-Breakers, Group Installations (600 V AC) | 47 kA |
| | Any UL Listed Fuses or Circuit-Breakers, Motor Disconnect (480 V AC) | 65 kA |
| | Any UL Listed Fuses or Circuit-Breakers, Motor Disconnect (600 V AC) | 47 kA |
| | Any UL Listed Fuses or Circuit-Breakers, Motor Disconnect (600 V AC) | 47 kA |

kA

Any UL Listed Fuses or Circuit-Breakers, Tap Conductor Protection in
Group Installations (480Y / 277 V AC) 65 kA
Any UL Listed Fuses or Circuit-Breakers, Tap Conductor Protection in
Group Installations (600Y / 347 V AC) 47 kA

| | |
|---|--|
| Maximum Operating Voltage UL/CSA | Main Circuit 600 V AC |
| Full Load Amps Motor Use | (200 V AC) Three Phase 0.4 A (208 V AC) Three Phase 0.4 A (220 ... 240 V AC) Three Phase 0.4 A (440 ... 480 V AC) Three Phase 0.4 A (550 ... 600 V AC) Three Phase 0.4 A |
| Locked Rotor Amps | (200 V AC) Three Phase 2.4 A (208 V AC) Three Phase 2.4 A (220 ... 240 V AC) Three Phase 2.4 A (440 ... 480 V AC) Three Phase 2.4 A (550 ... 600 V AC) Three Phase 2.4 A |
| General Use Rating UL/CSA | (600 V AC) 0.4 A |
| Connecting Capacity Main Circuit UL/CSA | Flexible 1/2x 16-12 AWG Stranded 1/2x 16-12 AWG |
| Tightening Torque UL/CSA | Main Circuit 10 ... 12 in-lb |

Environmental

| | |
|--|---|
| Ambient Air Temperature | Around the Enclosure 0 ... +40 °C Operation -25 ... +70 °C Operation Compensated -25 ... +60 °C Storage -50 ... +80 °C |
| Ambient Air Temperature Compensation | Yes |
| Maximum Operating Altitude Permissible | 2000 m |
| Resistance to Shock acc. to IEC 60068-2-27 | 11 ms Pulse 25g |
| Resistance to Vibrations | 5g 3 ... 150 Hz |

Material Compliance

| | |
|---|--|
| Conflict Minerals Reporting Template (CMRT) | 9AKK108467A5658 |
| REACH Declaration | 1SAA963005-4502 |
| RoHS Information | 1SAA963006-4502 |
| RoHS Status | Following EU Directive 2011/65/EU and Amendment 2015/863 July 22, 2019 |
| Toxic Substances Control Act - TSCA | 2CMT2023-006539 |
| WEEE B2C / B2B | Business To Business |
| WEEE Category | 5. Small Equipment (No External Dimension More Than 50 cm) |

Circular Value

| | |
|--------------------------|-----------------|
| End of Life Instructions | 1SAC200332H0001 |
|--------------------------|-----------------|

Certificates and Declarations

| | |
|-------------------------------------|--|
| A2L Certificate – IEC | 1SAA963000-4601 |
| ABS Certificate | 1SAA963001-0101 |
| ATEX Certificate | 1SAA963000-3902 |
| BV Certificate | 1SAA963001-0202 |
| CB Certificate | 1SAA963002-2002 1SAA963007-2002 |
| CCC Certificate | 2020980307003526 2020980307003041 |
| CQC Certificate | CQC2010010307387700 CQC2019010307243864 |
| Cut-off Current Characteristic | 1SAM300508F0001 1SAM300508F0003 |
| Declaration of Conformity - CCC | 2020980307003526 2020980307003041 |
| Declaration of Conformity - CE | 1SAD101100-3402 |
| Declaration of Conformity - UKCA | 1SAD201100-3402 |
| DNV GL Certificate | 1SAA963001-0304 |
| EAC Certificate | 1SAA963000-2701 |
| i ² t Characteristic | 1SAM300507F0001 1SAM300507F0003 |
| IECEX Certificate | 1SAA963000-4001 |
| KC Certificate | 1SAA963002-1502 |
| LR Certificate | 1SAA963001-0502 |
| RINA Certificate | 1SAA963002-0802 |
| RMRS Certificate | 1SAA918000-0704 |
| UL Certificate | E137861-20090225 E345003-20090225 |

Container Information

| | |
|-----------------------------------|-----------------|
| Package Level 1 Units | box 1 piece |
| Package Level 1 Width | 92 mm |
| Package Level 1 Depth / Length | 95 mm |
| Package Level 1 Height | 50 mm |
| Package Level 1 Gross Weight | 0.23 kg |
| Package Level 1 EAN | 4013614400032 |
| Package Level 2 Units | carton 40 piece |
| Package Level 2 Width | 280 mm |
| Package Level 2 Depth / Length | 395 mm |
| Package Level 2 Height | 210 mm |
| Package Level 2 Gross Weight | 9.586 kg |
| Package Level 2 EAN | 4013614408939 |

Classifications

| | |
|-------------------------------|---|
| Object Classification Code | F |
| ETIM 4 | EC000074 - Motor protective circuit-breaker |
| ETIM 5 | EC000074 - Motor protective circuit-breaker |
| ETIM 6 | EC000074 - Motor protection circuit-breaker |

| | |
|------------------------------------|---|
| ETIM 7 | EC000074 - Motor protection circuit-breaker |
| ETIM 8 | EC000074 - Motor protection circuit-breaker |
| eClass | V11.0 : 27370401 |
| UNSPSC | 39121521 |
| IDEA Granular Category Code (IGCC) | 4731 >> Manual Starters |
| E-Number (Finland) | 3705987 |
| E-Number (Sweden) | 3112119 |

Accessories

| Identifier | Description | Type | Quantity | Unit Of Measure |
|-----------------|--|-----------|----------|-----------------|
| 1SAM201901R1001 | HKF1-11 Aux.-contact for front mounting | HKF1-11 | 1 | piece |
| 1SAM201901R1201 | HKF1-11K Aux.-contact for frontmounting with Push-In terminals | HKF1-11K | 1 | piece |
| 1SAM201901R1002 | HKF1-20 Aux.-contact 2NO, front mounting | HKF1-20 | 1 | piece |
| 1SAM201901R1202 | HKF1-20K Aux.-contact for frontmounting with Push-In terminals | HKF1-20K | 1 | piece |
| 1SAM201901R1004 | HKF1-01 Aux.-contact for front mounting | HKF1-01 | 1 | piece |
| 1SAM201901R1003 | HKF1-10 Aux.-contact for front mounting | HKF1-10 | 1 | piece |
| 1SAM201902R1002 | HK1-20 Aux.-contact 2 NO | HK1-20 | 1 | piece |
| 1SAM201902R1202 | HK1-20K Aux.-contact 2 NO with Push-In terminals | HK1-20K | 1 | piece |
| 1SAM201902R1001 | HK1-11 Aux.-contact 1 NO + 1 NC | HK1-11 | 1 | piece |
| 1SAM201902R1201 | HK1-11K Aux.-contact 1 NO + 1 NC with Push-In terminals | HK1-11K | 1 | piece |
| 1SAM201902R1003 | HK1-02 Aux.-contact 2 NC | HK1-02 | 1 | piece |
| 1SAM201902R1203 | HK1-02K Aux.-contact 2 NC with Push-In terminals | HK1-02K | 1 | piece |
| 1SAM201902R1004 | HK1-20L Aux.-cont. w. 2 lead contacts 2 NO | HK1-20L | 1 | piece |
| 1SAM201902R1204 | HK1-20LK Aux.-cont. w. 2 leading contacts 2 NO, with Push-In terminals | HK1-20LK | 1 | piece |
| 1SAM201903R1002 | SK1-20 Signaling Contact 2 NO | SK1-20 | 1 | piece |
| 1SAM201903R1202 | SK1-20K Signaling Contact 2 NO with Push-In terminals | SK1-20K | 1 | piece |
| 1SAM201903R1005 | SK1-20AR Signaling Contact, 2NO with screw terminals | SK1-20AR | 1 | piece |
| 1SAM201903R1205 | SK1-20ARK Signaling Contact, 2NO with Push-in Spring terminals | SK1-20ARK | 1 | piece |
| 1SAM201903R1001 | SK1-11 Signaling Contact 1 NO + 1 NC | SK1-11 | 1 | piece |
| 1SAM201903R1201 | SK1-11K Signaling Contact 1 NO + 1 NC with Push-In terminals | SK1-11K | 1 | piece |
| 1SAM201903R1004 | SK1-11AR Signaling Contact, 1NO+1NC with screw terminals | SK1-11AR | 1 | piece |
| 1SAM201903R1204 | SK1-11ARK Signaling Contact, 1NO+1NC with Push-in Spring terminals | SK1-11ARK | 1 | piece |
| 1SAM201903R1003 | SK1-02 Signaling Contact 2 NC | SK1-02 | 1 | piece |
| 1SAM201903R1203 | SK1-02K Signaling Contact 2 NC with Push-In terminals | SK1-02K | 1 | piece |
| 1SAM201903R1006 | SK1-02AR Signaling Contact, 2NC with screw terminals | SK1-02AR | 1 | piece |
| 1SAM201903R1206 | SK1-02ARK Signaling Contact, 2NC with Push-in Spring terminals | SK1-02ARK | 1 | piece |
| 1SAM301901R1002 | CK1-20 Short-Circuit Signaling Contact 2 NO | CK1-20 | 1 | piece |
| 1SAM301901R1001 | CK1-11 Short-Circuit Signaling Contact 1 NO + 1 NC | CK1-11 | 1 | piece |
| 1SAM301901R1003 | CK1-02 Short-Circuit Signaling Contact 2 NC | CK1-02 | 1 | piece |

| | | | | |
|-----------------|---|-------------|---|-------|
| 1SAM201910R1001 | AA1-24 Shunt Trip 20-24V | AA1-24 | 1 | piece |
| 1SAM201910R1002 | AA1-110 Shunt Trip 110V | AA1-110 | 1 | piece |
| 1SAM201910R1003 | AA1-230 Shunt Trip 200-240V | AA1-230 | 1 | piece |
| 1SAM201910R1004 | AA1-400 Shunt Trip 350-415V | AA1-400 | 1 | piece |
| 1SAM201904R1010 | UA1-20 Undervoltage release 20V 50Hz / 24V 60 Hz | UA1-20 | 1 | piece |
| 1SAM201904R1001 | UA1-24 Undervoltage release 24 V | UA1-24 | 1 | piece |
| 1SAM201904R1002 | UA1-48 Undervoltage release 48V | UA1-48 | 1 | piece |
| 1SAM201904R1003 | UA1-60 Undervoltage release 60V | UA1-60 | 1 | piece |
| 1SAM201904R1004 | UA1-110 Undervoltage release 110V 110V 50Hz/120V 60Hz | UA1-110 | 1 | piece |
| 1SAM201904R1008 | UA1-208 Undervoltage release 208V 60Hz | UA1-208 | 1 | piece |
| 1SAM201904R1005 | UA1-230 Undervoltage release 230 V 50 Hz / 240 V 60 Hz | UA1-230 | 1 | piece |
| 1SAM201904R1006 | UA1-400 Undervoltage release 400V | UA1-400 | 1 | piece |
| 1SAM201904R1007 | UA1-415 Undervoltage release 415V 415V 50Hz/480V 60Hz | UA1-415 | 1 | piece |
| 1SAM201904R1009 | UA1-575 Undervoltage release 575V 60Hz | UA1-575 | 1 | piece |
| 1SAM201906R1102 | PS1-2-0-65 3-phase busbar for 2 MS116 / MS132, Ie=65A | PS1-2-0-65 | 1 | piece |
| 1SAM201906R1112 | PS1-2-1-65 3-phase busbar for 2 MS116 / MS132 with 1 HK/SK, Ie=65A | PS1-2-1-65 | 1 | piece |
| 1SAM201906R1122 | PS1-2-2-65 3-phase busbar for 2 MS116 / MS132 with 2 HK/SK, Ie=65A | PS1-2-2-65 | 1 | piece |
| 1SAM201916R1103 | PS1-3-0-100 3-phase busbar for 3 MS116 / MS132, Ie=100A | PS1-3-0-100 | 1 | piece |
| 1SAM201906R1103 | PS1-3-0-65 3-phase busbar for 3 MS116 / MS132, Ie=65A | PS1-3-0-65 | 1 | piece |
| 1SAM201916R1113 | PS1-3-1-100 3-phase busbar for 3 MS116 /MS132 with 1 HK/SK, Ie=100A | PS1-3-1-100 | 1 | piece |
| 1SAM201906R1113 | PS1-3-1-65 3-phase busbar for 3 MS116 / MS132 with 1 HK/SK, Ie=65A | PS1-3-1-65 | 1 | piece |
| 1SAM201916R1123 | PS1-3-2-100 3-phase busbar for 3 MS116 /MS132 with 2 HK/SK, Ie=100A | PS1-3-2-100 | 1 | piece |
| 1SAM201906R1123 | PS1-3-2-65 3-phase busbar for 3 MS116 / MS132 with 2 HK/SK, Ie=65A | PS1-3-2-65 | 1 | piece |
| 1SAM201916R1104 | PS1-4-0-100 3-phase busbar for 4 MS116 / MS132, Ie=100A | PS1-4-0-100 | 1 | piece |
| 1SAM201906R1104 | PS1-4-0-65 3-phase busbar for 4 MS116 / MS132, Ie=65A | PS1-4-0-65 | 1 | piece |
| 1SAM201916R1114 | PS1-4-1-100 3-phase busbar for 4 MS116 /MS132 with 1 HK/SK, Ie=100A | PS1-4-1-100 | 1 | piece |
| 1SAM201906R1114 | PS1-4-1-65 3-phase busbar for 4 MS116 / MS132 with 1 HK/SK, Ie=65A | PS1-4-1-65 | 1 | piece |
| 1SAM201906R1124 | PS1-4-2-65 3-phase busbar for 4 MS116 / MS132 with 2 HK/SK, Ie=65A | PS1-4-2-65 | 1 | piece |
| 1SAM201916R1105 | PS1-5-0-100 3-phase busbar for 5 MS116 / MS132, Ie=100A | PS1-5-0-100 | 1 | piece |
| 1SAM201906R1105 | PS1-5-0-65 3-phase busbar for 5 MS116 / MS132, Ie=65A | PS1-5-0-65 | 1 | piece |
| 1SAM201916R1115 | PS1-5-1-100 3-phase busbar for 5 MS116 /MS132 with 1 HK/SK, Ie=100A | PS1-5-1-100 | 1 | piece |
| 1SAM201906R1115 | PS1-5-1-65 3-phase busbar for 5 MS116 / MS132 with 1 HK/SK, Ie=65A | PS1-5-1-65 | 1 | piece |
| 1SAM201906R1125 | PS1-5-2-65 3-phase busbar for 5 MS116 / MS132 with 2 HK/SK, Ie=65A | PS1-5-2-65 | 1 | piece |
| 1SAM201907R1101 | S1-M1-25 3-phase power infeed block Flat, for MS116 / MS132, 25mm ² | S1-M1-25 | 1 | piece |
| 1SAM201907R1102 | S1-M2-25 3-phase power infeed block High, for MS116 / MS132, 25mm ² | S1-M2-25 | 1 | piece |

| | | | | |
|-----------------|---|-----------|---|-------|
| 1SAM201907R1103 | S1-M3-25 3-phase power infeed block Flat, for MS116 / MS132, 25mm ² , Type E | S1-M3-25 | 1 | piece |
| 1SAM201913R1103 | S1-M3-35 3-phase power infeed block Flat, for MS116 / MS132, 35mm ² , Type E | S1-M3-35 | 1 | piece |
| 1SAM201914R1002 | S1-PB1-25 1-phase power infeed block for MS116 / MS132 / MS132-T, 25mm ² , IEC | S1-PB1-25 | 1 | piece |
| 1SAM301911R1001 | TS1-M3-S1 Terminal Spacer MS132 Size 1 For MS/MO132-0.16 - MS/MO132-10 Type E | TS1-M3-S1 | 1 | piece |
| 1SAM301912R1001 | TS1-M3-S2 Terminal Spacer MS132 Size 2 For MS/MO132-12 - MS/MO132-32 Type E | S1-M3-S2 | 1 | piece |
| 1SAM201908R1001 | BS1-3 Protection Cover for busbars empty places | BS1-3 | 1 | piece |
| 1SAM201909R1001 | FS116 Screw fixing kit for MS116, MS/MO132 10 pieces packed | FS116 | 1 | piece |
| 1SAM201914R1001 | PB1-1-32 phase connecting link for MS116 / MS132 / MS132-T, Ie=32A | PB1-1-32 | 1 | piece |
| GJF1101903R0002 | SA2 Terminals and Installation Material | SA2 | 1 | piece |
| 1SAM201911R1012 | IB132-F Enclosure, GY/RD, IP65 3 times lockable | IB132-F | 1 | piece |
| 1SAM201911R1010 | IB132-G Enclosure, GY/BK, IP65 Standard version, 3 times lockable | IB132-G | 1 | piece |
| 1SAM201911R1011 | IB132-Y Enclosure, RD/YE, IP65 Emergency-STOP, 3 times lockable | IB132-Y | 1 | piece |
| 1SAM201912R1010 | DMS132-G Door Mounting Kit, GY/BK, IP65 Standard version, 3 times lockable | DMS132-G | 1 | piece |
| 1SAM201912R1011 | DMS132-Y Door Mounting Kit, RD/YE, IP65 Emergency-STOP, 3 times lockable | DMS132-Y | 1 | piece |
| 1SAM201909R1021 | MSAH1 Shaft Supporter suitable for MS116, MS132/MO132 | MSAH1 | 1 | piece |
| 1SAM201920R1011 | MSHD-LTB Handle, IP64, black, 3 times lockable, defeatable, 0-TRIP-I | MSHD-LTB | 1 | piece |
| 1SAM201920R1012 | MSHD-LTY Handle, IP64, red/yellow, 3 times lockable, defeatable, 0-TRIP-I | MSHD-LTY | 1 | piece |
| 1SAM101923R0002 | MSMN Driver w. screw for manual motor starters, 6x6 | MSMN | 1 | piece |
| 1SAM101923R0012 | MSMNO Driver w/o coding w. screw for manual motor starters, 6x6 | MSMNO | 1 | piece |
| 1SCA101647R1001 | OXS6X85 SHAFT | OXS6X85 | 1 | piece |
| 1SCA108043R1001 | OXS6X105 SHAFT | OXS6X105 | 1 | piece |
| 1SCA101655R1001 | OXS6X130 SHAFT | OXS6X130 | 1 | piece |
| 1SCA101659R1001 | OXS6X180 SHAFT | OXS6X180 | 1 | piece |

Categories

Low Voltage Products and Systems → Circuit Breakers → Manual Motor Starters

Low Voltage Products and Systems → Control Products → Manual Motor Starters → Manual Motor Starters

